

T2MK7F8DQAP (Kit)


Access & Power Integration Solution for Mercury

TROVE[™]

Altronix T2MK7F8DQAP kit consists of Trove2 enclosure, TM2 Mercury/Altronix backplane and TMV2 Mercury/Altronix door backplane with one 24VDC @ 10A power supply/charger; one voltage regulator supplies 12VDC and 24VDC to one eight (8) PTC protected dual input/output network/managed access control module and one eight (8) PTC protected dual input/output network/managed power distribution module. Also included is a 5-Port hardened switch board. This kit also accommodates various combinations of Mercury/Lenel* boards for up to eight (8) doors in a single enclosure. Trove simplifies board layout and wire management, reduces installation time and labor costs.

***Also compatible with these authentic Mercury partners:**

AccessNsite, Avigilon, BadgePass, BluBox, Feenics, Genetec, Identicon, IMRON, Johnson Controls, Kastle, Keri Systems, Lenel/S2, LockState, Maxxess, Midpoint Security, NLSS, Open Options, Panasonic Video Insight, Quintron, RS2, Schneider Electric, Vanderbilt

**T2MK7F8DQAP***Mercury boards are not included***Key Features**

- 24VDC power supply/charger
- Accommodates the following Mercury controllers:
LP1502, MR52, MR16IN, MR16OUT, LP2500, MUX8,
MR62e, LP1501, MR50, and Genetec Synergis Cloud Link
- Convenient knockout configuration:
 - One (1) single knockout 2.415" (2" Conduit)
 - Sixteen (16) double knockouts
1.362" (1" Conduit) / 1.115" (3/4" Conduit)
- Enclosure accommodates up to four (4) 12VDC/12AH batteries
- 16 gauge galvanized steel backplane simplifies board layout and wire management
- Supervision
 - AC Fail
 - Low Battery and Battery Presence
 - Low power shutdown
- CE European Conformity
- Lifetime Warranty*

**Altronix Power Supply/Chargers and Sub-Assemblies only*

Specifications

Power Supply/Charger (eFlow104NB):

Input	
Voltage	120VAC, 60Hz, 4.5A max.
Input Fuse	6.5A/250V
Outputs	
Voltage	24VDC
Current	10A continuous
Auxiliary	Class 2 power-limited @ 1A (unswitched)
Other	Overvoltage protection. Filtered and regulated

Battery Charging

Capacity	12VDC/12AH (4 within enclosure) 40AH/65AH (requires separate enclosure)
Type	Sealed lead acid or gel type
Failover	Upon AC loss, instantaneous
Batteries are sold separately	

Fire Alarm Disconnect

Supervised	Latching or non-latching
EOL	10K Resistor

Supervision

AC Failure	Form "C" contacts
Battery	Form "C" contacts
Low DC Power Shutdown	
Shuts down DC output terminals if battery voltage drops below 70-75% for 24V units. Prevents deep battery discharge	

Indicators (LED)

Input	120VAC is present
DC Output	Powered

Network Access Power Controller (LINQ8ACMCB):

Input	
Voltage	24VDC from eFlow104NB and 12VDC from VR6
Input PTCs	9A

Outputs

PTC protected outputs	
Any of the eight (8) PTC protected power outputs are selectable to follow power Input 1 or Input 2	
Individual outputs may be set to OFF position for servicing	
Output PTCs:	2.5A

Programming Features:

- Eight (8) Programmable Outputs:**
- Fail-safe, fail-secure or auxiliary outputs
 - Input controlled or manually controlled through software
 - High (over) and low (under) voltage and current monitoring by output
 - Multiple outputs may be programmed to be triggered by a single input
 - Battery back-up by output

Eight (8) Programmable Trigger Inputs:

- Normally open (NO), Normally closed (NC) or Open collector sink inputs
- Wet Input (5VDC - 24VDC) with 10k resistor
- Any combination of the above

Other Programmable Trigger Inputs:

- Monitor power supply(ies) input for voltage and current limits (high/low)
- Input and output current calibration, Programmable timer events
- Programmable user levels, Enable or disable alerts by type
- Programmable alert reporting delay

Indicators (LED)

Green AC LED:	indicates AC trouble condition
Green BAT LED:	indicates battery trouble condition
Green FACP LED:	indicates FACP disconnect is triggered
Flashing Blue Heartbeat LED:	indicates network connection
Individual OUT1 - OUT8 Red LEDs:	indicate outputs are triggered
Individual Voltage LEDs:	indicate 12VDC (Green) or 24VDC (Red)

Network Power Distribution Module (LINQ8PDCB):

Input	
Voltage	24VDC from eFlow104NB and 12VDC from VR6
Input Fuses	15A/32V

Outputs

PTC protected outputs	
Any of the eight (8) PTC protected power outputs are selectable to follow power Input 1 or Input 2	
Individual outputs may be set to OFF position for servicing	
Output PTCs:	2.5A

Status Monitoring

Power Supply output voltage and load, Voltage and load of each output	
FACP trigger and reset status, Unit temperature (Celsius)	
Power Supply AC and Battery status, Battery health	

Reporting:

Windows Dashboard Alert messages	
E-mail notifications, Event Log tracks history	

Indicators (LED)

Bat Local	Charging current status
FACP	Triggered / Released
Input	Input signal
Out1 - Out8	Output status

5-Port Hardened Switch (NetWay5B):

Input	12VDC, current draw: 150mA
Ethernet Ports:	
Five (5) 10/100/1000 Mbps data ports	
Connectivity: RJ45, auto-crossover	
Wire type: 4-pair CAT5 or better structured cable	
Distance: up to 100m	
Speed: 10/100/1000 Mbps, half/full duplex, auto negotiation	

Indicators (LED)

Individual PoE On LEDs for each port	
Individual IP Link status, 10/100Base-T/active LEDs for each port	

Voltage Regulator (VR6):

Input	
Voltage	24VDC from eFlow104NB
Output	
Voltage	12VDC
Current	6A continuous
Other	Surge suppression

Indicators (LED)

Input	24VDC is present
Output	Powered

T2MK7F8DQAP Kit:

Agency Listings

CE	European Conformity
----	---------------------

Physical and Environmental

Dimensions (H x W x D)	
Enclosure: 27.25" x 21.5" x 6.5" (692.2mm x 546.1mm x 165.1mm)	
Shipping: 32.5" x 26.5" x 11.125" (825.5mm x 673.1mm x 282.6mm)	

Weight (approx.)

Product	56.3 lb. (25.5 kg)
Shipping	61.3 lb. (27.8 kg)

Temperature

Operating	0°C to 49°C (32°F to 120°F)
Storage	- 20°C to 70°C (- 4°F to 158°F)

Relative Humidity


85% +/- 5%

BTU/Hr (approx.):

128 BTU/Hr.

Access Controller Position Chart for the Following Models:

Mercury	Pem Mounting
LP2500, MUX8	(A)
LP1502, LP4502, MR52, MR16IN, MR16OUT	(B)
LP1501, MR62e	(C)
MR50	(D)



Accessories (order separately)



WM5

WM5, WM25, WM100 - Magnetic Cable Tie Mounts

Altronix WM5, WM25, and WM100 are packs of 5, 25 or 100 magnetic cable tie mounts respectively. They accommodate standard zip ties or velcro straps. These are ideal for wire management in our Trove series.



Mounting Magnet

MM4, MM8, MM12, MM24 - Magnetic Mounting Solution

Altronix mounting magnets accommodate screws and nylon standoffs to allow for mounting various boards/ accessories in any metal enclosure or backplane.



BR1

BR1 - Sub-Assembly Mounting Bracket

Altronix BR1 mounting bracket is compatible with Altronix Maximal and Trove enclosures. It allows to mount one (1) PD4UL(CB), PD8UL(CB), ACM4(CB), MOM5, VR6, PDS8, NetWay5B or LINQ8PD(CB) sub-assembly on the enclosure's inside wall, saving valuable space.



Trove2BWC
with
batteries



Trove2BWC
with
wires

TROVE2BWC - Battery/Wire Trough Enclosure

Altronix Trove2BWC is a dual-purpose enclosure that can be used as wiring trough or battery cabinet when mounted above or below of the Trove2 integrated power and access solution. The knockouts on the Trove2BWC have been strategically placed to line up with the Trove2 allowing for easy conduit connections between cabinets. Trove2BWC includes cam locks and 2 tamper switches to ensure access to wiring and batteries is secure.

Dimensions and Drawing

Dimensions (H x W x D approximate)

27.25" x 21.5" x 6.5" (692.2mm x 546.1mm x 165.1mm)

