

R1002ULADA

Rack Mountable NAC Power Extender

Altronix R1002ULADA is a space-saving 10A remote power supply/battery charger for fire signaling applications such as Notification Appliance Circuits expansion (strobes and horns) meeting ADA requirements. The rack mount drawer configuration is designed to be deployed where wall space is limited or may not be an option. R1002UALDA may be connected to any 12 or 24 volt Fire Alarm Control Panel (FACP). This unit delivers electronically regulated and filtered 24 volt power to Class B or Class A NAC loop circuits. The 10A max. alarm current can be divided between the four (4) outputs for powering NAC devices. All outputs may be programmed for Input to Output Follower Mode (output will follow input). In non-alarm condition independent loop supervision for Class A and/or Class B FACP NAC circuits is provided Two (2) FACP signaling outputs can be employed and directed to control supervision and power delivery to any combination of the four (4) outputs.



Key Features

- Compatible with 12VDC or 24VDC fire panels
- Programmable supervised indicating circuit outputs (Class A and Class B)
- Sync protocols include Potter/Amseco, Gentex[®],
 System Sensor[®], and CooperWheelock[®]
- Additional aux. output rated @ 1A

- Temporal Code 3, Steady Mode, Input to Output Follower Mode
- Signal circuit trouble memory
- Ground fault detection
- Built-in charger for sealed lead acid or gel type batteries
- Modular 2U standard EIA 19" rack mount chassis

Accessories (order separately)



RE2R Rack Mount Battery Enclosure
accommodates up to four (4) 12VDC/7AH batteries



R1002ULADA

Rack Mountable NAC Power Extender

Specifications -

Input

Voltage 120VAC, 60Hz, 5A

Two (2) Class A or two (2) Class B inputs

Two (2) NC dry contact trigger inputs

Input Ratings (INP1 and INP2):

8-30VDC 6.5mA max from FACP 12V 6.5mA, 24V 6.5mA from FACP

Output

Voltage 24VDC power-limited outputs Current 10A max. total alarm current 2.5A max. current per output

Auxiliary

Other Thermal and short circuit protection with

auto reset

Filtered and regulated outputs

Programmable Supervised Indicating Circuit Outputs:

Four (4) Class B, or Two (2) Class A, or One (1) Class A and Two (2) Class B

Battery Charging

Sealed lead acid or gel type Type Failover Upon AC loss, instantaneous

Batteries are sold separately

Supervision

AC Failure Form "C" contacts Battery Form "C" contacts

Indicators (LED)

AC Power (Green) Input voltage is present

Powered DC Output (Red) Logic Board Output status

(Red and Green)

Agency Listings

UL UL864 (Control Units and Accessories for

Fire Systems)

FΜ Factory Mutual Approved

CSFM California State Fire Marshal Approved

Special Features

- 2-wire horn/strobe Sync mode allows audible notification appliances (horns) and visual notification appliances (strobes) to

be silenced/deactivated at the same time

- Sync protocols include Potter/Amseco, Gentex[®], System Sensor®, and CooperWheelock®

- Temporal Code 3, Steady Mode, Input to Output Follower Mode (maintains synchronization of notification appliances circuit)

- Compatible with 12VDC or 24VDC fire panels.

- Output loop supervision steered to Input 1 or Input 2

- Signal circuit trouble memory

(helps identify intermittent loop problems)

- Common trouble input and output for external trouble signals tie-in

- Ground fault detection.

Physical and Environmental

Dimensions (H x W x D)

Modular 2U standard FIA 19" rack mount chassis

Enclosure: 3.25" x 19.0" x 26.5" (82.6mm x 482.6mm x 673.1mm) Shipping: 31" x 23" x 8.25" (787.4mm x 584.2mm x 209.6mm)

Weight (approx.)

Product: 20 lb. (9.07 kg) Shipping: 25 lb. (11.34 kg)

Temperature

Operating: 0°C to 49°C (32°F to 120°F) - 20°C to 70°C (- 4°F to 158°F) Storage:

Relative Humidity 85% +/- 5% BTU/Hr. (approx.): 49 BTU/Hr.



R1002ULADA

Rack Mountable NAC Power Extender

Dimensions and Drawing -

Dimensions (H x W x D approximate)

13.25" x 19.0" x 26.5" (82.6mm x 482.6mm x 673.1mm)

