



NetWaySP1P

Powered

Media Converter/Repeater



Installation Guide

Overview:

Altronix NetWaySP1P converts 1000 Mbps ethernet to Fiber (1000Base-X/SX/LX) and provides PoE.

Features:

Agency Listings:

- UL/cUL Listed for Information Technology Equipment (UL 60950-1).
- CE approved.

Input:

- 24VDC @ 1.5A, 56VDC @ 0.75A (30W).
- 24VDC @ 1.0A, 56VDC @ 0.5A (15W).

Fiber Port:

- One (1) 1Gb SFP port.
- Use with SFP module 1000Base-X (1Gb), compliant to Class 1 laser product (not included).

Ethernet:

- IEEE 802.3at (30W) compliant.
- Wire type: 4-pair CAT5e and higher.
- Connectivity: RJ45, auto-crossover.
- Speed: Gigabit (1000Mbps).
- Distance: up to 100m.

LED Indicators:

- **Yellow and Green LEDs** (RJ45 jack):
IP Link status, 10/100/1000 Base-T/active.
- **Green Pwr In LED:**
Indicates unit is powered.
- **Green PoE LED:**
Indicates PoE present.
- **Green SFP (Fiber) LED:**
Indicates SFP connection.

Environmental:

- Refer to *Environmental Conditions on page 3.*

Dimensions (W x L x H approx.):

3.375" x 3.8" x 1"
(85.7mm x 96.52mm x 25.4mm).

Installation Instructions:

Unit is powered via 24VDC-56VDC. NetWaySP1P is not intended to be connected to outside plant leads and should be installed indoors within the protected premises.

1. Mount NetWaySP1P in desired location utilizing the mounting hole (*Fig. 1a, pg. 2*). Use a proper fastener and/or wall anchor when securing NetWaySP1P with screw through its mounting hole to the wall.


Note: Earth ground can be used, if needed, for high transient or outdoor environments.

If used, insert an Earth ground wire (included with product) into the internal ground terminal until secured (a slight tug can check stability) & fasten the free end to a chassis earth ground.

If earth ground is not attached and needed, refer to Fig.1b, pg.2 for manual placement.

2. Connect 24VDC-56VDC power source to terminals marked [24-56VDC – Input +].
Terminals accommodate up to 12 AWG wires.
3. Connect structured cable from port marked [PoE+ Output] on NetWaySP1P to a PoE device (*Fig. 2, pg. 2*).
4. Connect fiber optic cable to a fiber SFP module. Connect the module to the port marked [SFP] on the NetWaySP1P. Connect the other end of fiber cable to an SFP module of a remote device. SFP LED will illuminate indicating data connection (*Fig. 2, pg. 2*).

Fig. 1



Typical Applications:

Fig. 2




Fig. 3







Fig. 4



Technical Specifications:

Parameter	Description		
Ports	One (1) 1Gb SFP port. One (1) Gigabit (1000Mbps) Ethernet port.		
Input power requirements	24VDC @ 1.5A, 56VDC @ 0.75A (30W / PoE+). 24VDC @ 1.0A, 56VDC @ 0.5A (15W / PoE).		
Indicators	Green Pwr In LED : Indicates unit is powered. Green PoE LED : Indicates PoE present. Green SFP (Fiber) LED : Indicates SFP connection.		
Environmental Conditions	Input	Output (Watts)	Temperature
	24VDC	15W	- 40°C to 65°C (- 40°F to 149°F)
		20W	- 40°C to 60°C (- 40°F to 140°F)
		25W	- 40°C to 55°C (- 40°F to 131°F)
		30W	- 40°C to 45°C (- 40°F to 113°F)
	56VDC	25W	- 40°C to 75°C (- 40°F to 167°F)
		30W	- 40°C to 70°C (- 40°F to 158°F)
Storage: - 40°C to 75°C (- 40°F to 167°F).			
Relative Humidity: 85% +/- 5%. Operating Altitude: - 304.8 to 2,000m.			
Regulatory Compliance	 UL/cUL Listed for Information Technology Equipment (UL 60950-1). I.T.E. 43KC  CE European Conformity.		
Weights (approx.)	Product: 0.25 lb. (0.11 kg) Shipping: 0.3 lb. (0.14 kg).		

Recommended Altronix SFP Modules:

Altronix P1MM, P1SM10, P1AB2K and P1GCE are hot-pluggable SFP fiber transceiver modules and are readily usable with all Altronix Spectrum fiber optic equipment for 1Gb transmission rates.

P1MM - For use with Multi-Mode Fiber for distances up to 550m.

P1SM10 - For use with Single-Mode Fiber for distances up to 10km.

P1AB2K - For use with Single Strand Single-Mode Fiber for distances up to 2km.

P1GCE - For use with CAT5e or better for distances up to 100m.

Altronix is not responsible for any typographical errors.

140 58th Street, Brooklyn, New York 11220 USA | phone: 718-567-8181 | fax: 718-567-9056
website: www.altronix.com | e-mail: info@altronix.com | Lifetime Warranty
NetWaySP1P Rev. 070717 H04W

